ZERRA

MP7000 Scanner Scale

DELIVER AN UNSURPASSED CHECKOUT EXPERIENCE FOR CUSTOMERS AND CASHIERS IN THE BUSIEST STORES

Meet the demands of your highest-volume POS lanes with Zebra MP7000 next generation multi-plane 1D/2D imager. The MP7000 is loaded with features that take scanning performance and simplicity to the next level, enabling faster-than-ever checkout in cashier-manned and self-checkout lanes, improving cashier productivity, POS throughput and the shopper experience. A smart investment, the MP7000 offers an unmatched industry-best total cost of ownership (TCO) by delivering maximum uptime and minimum power consumption in an easy-to-service design with fewer parts and components. And with Zebra's complimentary powerful management applications, you can remotely manage all of your MP7000s, no matter where they are located.



FASTEST CHECKOUT PERFORMANCE

Unparalleled Scanning Performance in the Busiest Checkout Lanes

Keep checkout lanes moving and process more transactions per shift. Our most advanced scanning technology enables cashiers to capture virtually every electronic and printed barcode instantly.

Large Scan Zone Maximizes Checkout Speed

The largest scan zone in its class allows your workers to simply swipe-and-go, boosting cashier productivity and your shoppers' checkout experience.

Customer Side Scanner Increases Productivity

With the optional side scanner, customers can simultaneously scan mobile coupons, loyalty cards and impulse buy items — without slowing down the cashier.

INDUSTRY BEST TCO

Easy to Deploy

The MP7000 is designed to easily fit into your existing cash wrap, providing a cost-effective path to deploying the latest POS technology in your checkout lanes.

Lowest Power Consumption in the Industry

Our intelligent illumination system consumes up to 60 percent less power than competitive devices, greatly reducing power consumption and cost.

Superior Durability for Maximum Uptime

With solid state technology, the MP7000 has no moving parts, providing the fewest failure points in this class. The result? Fewer repairs, maximum uptime and a low total cost of ownership (TCO).

Easy to Service

The MP7000 was designed with fewer components and parts and an upper housing that can be removed without tools. As a result, reliability is greatly improved, there are fewer parts to stock and less time is required for repair.

INNOVATION AT THE POS

Integrated support for Digimarc®

The ability to scan Digimarc-enhanced product packages from any angle drives faster retail checkout, reducing the time shoppers spend in line.

Image Capture Capability

The integrated camera system can capture images of checks, receipts, utility bills or items not on file.

Intelligent Illumination

The MP7000 illumination only activates when an item is in the scan zone. And since the illumination is recessed, it's practically invisible, easy on the eyes of your cashiers and your shoppers.

Integrated EAS support

Supports the Electronic Article Surveillance system you have in place today.

UNRIVALED MANAGEABILITY

Unprecedented Management Capability

With every Zebra MP7000, you get powerful complimentary management software for easy remote management of your entire scanner solution — scanner, scale and all attached peripherals, such as a handheld scanner. And with predictive diagnostics, the information you need to keep your MP7000 devices up and running is always at your fingertips.

MAXIMIZE THE SPEED AND QUALITY OF THE CHECKOUT EXPERIENCE IN THE BUSIEST STORES WITH THE MP7000.

For more information about the MP7000, visit www.zebra.com/MP7000 or access our global contact directory at www.zebra.com/contact

MP7000 Specifications

Dimensions	Long scanner and scanner/scale:
Difficusions	20 in. L x 11.5 in. W x 4.00 in. D x 5.00 in. H 506 mm L x 292 mm W x 102 mm D x 128 mm H
	Medium scanner and scanner/scale: $15.7 \text{ in. L} \times 11.5 \text{ in. W} \times 4.00 \text{ in. D} \times 5.00 \text{ in. H} \\ 398 \text{ mm L} \times 292 \text{ mm W} \times 102 \text{ mm D} \times 128 \text{ mm H}$
	Short scanner: 13.9 in. L x 11.5 in. W x 4.00 in. D x 5.00 in. H 351 mm L x 292 mm W x 102 mm D x 128 mm H
Weight	Long scanner: 14.6 lb/6.6 kg
	Long scanner/scale: 17.6 lb/8.0 kg
	Medium scanner: 12.6lb / 5.7 kg
	Medium scanner/scale: 15.7 lb/ 7.1 kg
	Short scanner: 12.1 lb/ 5.5 kg
Scale	30 lb. in 0.01 lb. increments/15 kg in 5 g increments Maximum static weight: 300 lb./136 kg
	Single-cable and dual-cable protocols
	Compatible with Mettler price computational scale
	Options:
	0-12 lb. in 0.005 lb. increments and 12-30 lb. in 0.01 lb. increments
	0-6 kg in 2 g increments and 6-15 kg in 5 g increments
	Single-head and dual-head remote scale display
Horizontal Glass	Sapphire; produce flip-up bar on scale models
User Interface	Soft touch capacitive pads (no buttons to break or wear out)
	Large two-color LED
	Beeper: adjustable volume and beep tones Four programmable buttons
Ports	One shared POS port for USB/RS-232/IBM RS-485
	Three USB peripheral ports
	Two powered RS-232 peripheral ports
	Checkpoint interlock port
	oneckpoint interiock port
	Remote scale display port
Power	
Power	Remote scale display port 12VDC from POS interface cable
Power	Remote scale display port 12VDC from POS interface cable (USB PlusPower or RS-232) Zebra PWR-BGA12V50W0WW power supply: 90-264 s (110-240 nominal),
Power	Remote scale display port 12VDC from POS interface cable (USB PlusPower or RS-232) Zebra PWR-BGA12V50W0WW power supply: 90-264 s (110-240 nominal), 47-63Hz (50-60 nominal) Power consumption:
Power USER ENVIRONMENT	Remote scale display port 12VDC from POS interface cable (USB PlusPower or RS-232) Zebra PWR-BGA12V50W0WW power supply: 90-264 s (110-240 nominal), 47-63Hz (50-60 nominal) Power consumption: Idle mode: 3.0 W (typical) Active mode: 5.5 W (typical), 6.0 W (maximum
	Remote scale display port 12VDC from POS interface cable (USB PlusPower or RS-232) Zebra PWR-BGA12V50W0WW power supply: 90-264 s (110-240 nominal), 47-63Hz (50-60 nominal) Power consumption: Idle mode: 3.0 W (typical) Active mode: 5.5 W (typical), 6.0 W (maximum
USER ENVIRONMENT	Remote scale display port 12VDC from POS interface cable (USB PlusPower or RS-232) Zebra PWR-BGA12V50W0WW power supply: 90-264 s (110-240 nominal), 47-63Hz (50-60 nominal) Power consumption: Idle mode: 3.0 W (typical) Active mode: 5.5 W (typical), 6.0 W (maximum only when illumination is on)

Туре	Multiple CMOS Array Imager
Illumination	Intelligent Illumination, controlled by item detection system
Sides Read/Scan Zone	Reading of linear and 2D codes in all planes
1D Symbologies	2 of 5 (Interleaved, Discrete, IATA, Chinese); Bookland EAN; Code 128; Code 39 (standard, full ASCII); Code 93; EAN128; EAN-13; EAN-8; GS1 DataBar (Omnidirectional, Truncated, Stacked); GS1 DataBar Expanded coupon; GS1 DataBar Limited; GS1 DataBar Expanded (regular, stacked) JAN 8; JAN-13; MSI/Plessey; TLC-39; Trioptic Code 39; UPC-A; UPC-E; UPC-E1; 2-digit Supplementals 5-digit Supplemental; Codabar; Pharmacode (Code 32)
2D Symbologies	Aztec; Datamatrix; MicroPDF417; MicroQR Code; PDF417; QR Code; Han Xin
Digimarc	Digimarc watermark technology
UTILITIES AND MANA	AGEMENT
123Scan	Programs scanner parameters, upgrades firmware, displays scanned barcode data, scanning statistics, battery health, asset data and prints reports. www.zebra.com/123scan
Symbol Scanner SDK	Generates a fully-featured scanner application, including documentation, drivers, test utilities and sample source code. www.zebra.com/scannersdkforwindows
Scanner Management Service (SMS)	Remotely manages your Zebra scanner and queries its asset information. www.zebra.com/sm
Loss Prevention	EAS Checkpoint supported: Checkpoint interlock via optional cable
	Sensormatic supported
	Zebra Scale Platter: Integrated horizontal and vertical platter for increased weighing area
PERIPHERALS AND A	ACCESSORIES
	ows self-scanning of barcodes on mobile phones, uy items); pole display; scale
WARRANTY	
is warranted against defect	ra's hardware warranty statement, the MP7000 s in workmanship and materials for a period of f shipment. For complete warranty statement, n/warranty
RECOMMENDED SER	RVICES
	ra OneCare Essential; Zebra's Service Authorization spare parts for third party repair)



NA and Corporate Headquarters +1 800 423 0442 inquiry4@zebra.com Asia-Pacific Headquarters +65 6858 0722 contact.apac@zebra.com

EMEA Headquarters zebra.com/locations mseurope@zebra.com

Latin America Headquarters +1 847 955 2283 la.contactme@zebra.com